

## Description

# COMPLEMENTARY SOURCE FOLLOWER CIRCUIT CONTROLLED BY BACK BIAS VOLTAGE

### CROSS REFERENCE TO RELATED APPLICATIONS

[0001] This application is a continuation-in-part of application Serial No. 10/064,491, filed July 22, 2002, and now abandoned.

### BACKGROUND OF INVENTION

[0002] This invention relates to a semiconductor circuit on a large scale integrated circuit(LSI). In particular, it relates to a complementary source follower circuit of a MOS (metal oxide semiconductor) LSI that is suitable for an output buffer of an analog circuit.

[0003] Figure 1 shows a conventional CMOS (complementary MOS) drain follower circuit. In Figure 1, there are two transistors, a P-channel MOSFET (metal oxide semiconductor field effect transistor) and an N-channel MOSFET.

Each transistor has a source (S), a drain (D), a gate (G), and a body (B). This circuit can be used to invert signals, i.e., to convert a logical "0" into a logical "1" and a logical "1" into a logical "0," where a logical "0" is represented by the voltage  $V_{ss}$  and a logical "1" is represented by the voltage  $V_{cc}$ . The logical "1" or "0" signal is supplied to "IN" and the inverted logical "0" or "1" signal is sent to "OUT." The voltages  $V_{ss}$  and  $V_{cc}$  are kept constant during the operation of the circuit. Each of the transistors should be "off" when the other transistor is "on" but there is some overlap when both transistors will be "on," resulting in a "DC path" with a current flow,  $I_d$ , from  $V_{cc}$  to  $V_{ss}$ . This current flow is wasted power.

[0004] Figure 2 illustrates the relationship between the voltage at IN in Figure 1 ( $V_{in}$  along the horizontal axis) and the voltage at OUT in Figure 1 ( $V_{out}$  along the right vertical axis) and shows that as  $V_{in}$  approaches the voltage  $V_{cc}$ ,  $V_{out}$  approaches the voltage  $V_{ss}$  and as  $V_{in}$  approaches the voltage  $V_{ss}$ ,  $V_{out}$  approaches the voltage  $V_{cc}$ . The left vertical axis gives the current  $I_d$  (dotted curve) that flows as  $V_{in}$  increases along the horizontal axis from  $V_{ss}$  to  $V_{cc}$  and shows that when  $V_{in}$  is about midway between  $V_{ss}$  and  $V_{cc}$  there is a current flow  $I_d$ , which is lost power.

- [0005] The circuit of Figure 1 is useful for processing digital signals because digital signals consist of a logical 0 or a logical 1, and intermediate levels where power is lost occur only during transitions between them. However, as circuits shrink, it is becoming possible to perform both digital and analog functions on a single chip, which is especially desirable for wireless and mobile applications.
- [0006] Figure 3 shows an example of an analog signal. This signal consists of many intermediate voltage levels. When an analog signal is inputted to conventional CMOS circuit, such as that of Figure 1, the current  $I_d$  flows almost constantly because the voltage is at intermediate levels so much of the time.
- [0007] Figure 4 shows a complementary source follower circuit similar to the complementary drain follower circuit of Figure 1, where the sources, rather than the drains, are connected to the "OUT" voltage. Figure 5 is similar to Figure 2 but shows (horizontal axis and right vertical axis) that as the INPUT voltage in Figure 4 increases from  $V_{ss}$  to  $V_{cc}$  the OUTPUT voltage  $V_{out}$  increases from  $V_{ss}$  to  $V_{cc}$ . Figure 5 also shows (horizontal axis and left vertical axis) that there is a small current loss  $I_d$  (dotted curve) at a voltage intermediate between  $V_{ss}$  and  $V_{cc}$ . The level of cur-

rent  $I_d$  depends on the threshold voltage conditions. When the voltage applied to the transistors does not exceed their threshold voltages, both transistors are in an off condition and there is no " $I_d$ " current flow. For that reason, source follower circuits are attractive for merged digital-analog systems.

[0008] Figure 6 shows a source follower circuit having an active load. But in the circuit of Figure 6, when the transistor is "on" a current steadily flows between  $V_{cc}$  and  $V_{ss}$ , which increases power consumption. Also, the driving power is low because the current is shared between both the active load and the output load.

[0009] In order to reduce the power consumption and the driving power loss, a complementary source follower circuit can be used as shown in Figure 7. This circuit can be realized using a bulk semiconductor substrate such as a single crystal silicon N-type or P-type substrate, but for a P-type substrate the source-to-body connection of the N-channel transistor is eliminated (as in Figure 7) and for an N-type substrate the source-to-body connection of the P-channel transistor is eliminated (not shown).

[0010] However, eliminating the source-to-body connection in Figure 7 results in non-linearity between the output volt-

ages of the two transistors because the characteristics of the two transistors are not symmetrical.

[0011] In U.S. Patent No. 5,463,240, a complementary source follower circuit on a common substrate is achieved by isolating each P-channel and N-channel transistor from the common semiconductor substrate. In laid open Japanese Patent No. 2000-323720 by the instant inventor, an SOI (silicon on insulator) substrate is used and in that invention no additional mask or circuit is needed, because on an SOI substrate each transistor can be isolated from other transistors and from the substrate.

[0012] As shown in Figure 8, the linear relationship between input voltage  $V_{in}$  and output voltage  $V_{out}$  shown in Figure 5 is offset when both transistors are "off" at the same INPUT voltage. Non-linearity occurs because the INPUT voltage is lower than the threshold voltages of the transistors. This creates a "dead gap" at an intermediate voltage between  $V_{ss}$  and  $V_{cc}$  where both transistors are "off" and the voltage at the OUTPUT node is open. This dead gap can be tolerated when the signal is digital, but it distorts an analog signal. Improvements in the linearity between the input signal and the output signal are needed in order to permit a source follower circuit to process analog signals.

[0013] The circuit shown in Figure 9 is similar to the circuit shown in Figure 4 except that a voltage  $V_{thN}$  is added to the input voltage  $V_{in}$  going to the N-channel MOSFET and a voltage  $V_{thP}$  is subtracted from the input voltage  $V_{in}$  going to the P-channel MOSFET. As shown in Figure 10, these shifts in the two input voltages shift the voltage output  $V_{out}$  to the dotted line, thereby eliminating the dead gap.

[0014] In U.S. Patent No.6, 333,623, a source follower circuit is used as a voltage regulator because a source follower circuit has low output impedance. In this patent, level shift circuits are also disclosed. In this patent, a level shift circuit is applied to the input node (IN) of the complementary source follower circuit to solve the dead gap problem. Also, a source follower circuit is used as a voltage regulator because a source follower circuit has low output impedance. In this patent, level shift circuits are also disclosed.

[0015] In the above patents, in order to realize complementary source follower circuits additional manufacturing processes are needed and, in order to solve dead gap problem, additional circuits, such as a level shift circuit, are needed.

## SUMMARY OF INVENTION

- [0016] An object of the present invention is to provide a high performance, area-efficient complementary source follower circuit that can be fabricated by conventional CMOS technology, without the need for special manufacturing processes or structural modifications.
- [0017] Another object of the present invention is to avoid the use of additional circuits and the placing of limitations on the use of the circuit and instead to employ standard devices available in high performance CMOS logic technology.
- [0018] Pursuant to these and other objectives, one embodiment of the present invention comprises a complementary source follower circuit having P-channel and N-channel MOSFETs, where the threshold voltage of each MOSFET is independently controlled by a back bias control circuit from which control signals are sent to each of the source and body terminals. In the circuit of this invention, a drain of one MOSFET is connected to the ground level and the drain of the other MOSFET is connected to the supply voltage, both gate terminals are connected to each other as an input node, and both source terminals are connected to each other as an output terminal node. There are no signal line connections from either source or either

drain to the body and there is no signal line connection from the back bias circuit to the drain.

[0019] A significant and novel feature of the present invention is that there is usually no need for an additional circuit such as a level shift circuit (though one can be used, if desired or needed), which results in less time delay. In addition, because each transistor's threshold voltage can be controlled over a wide range, the power consumption can be reduced when the circuit is in stand-by mode.

[0020] Another advantage of the present invention is that it can be used to eliminate of the dead gap.

[0021] In another embodiment of this invention, an SOI substrate is used.

[0022] In this invention, analog and digital signal circuits can be combined on one chip without any additional manufacturing processes such as masking.

#### **BRIEF DESCRIPTION OF DRAWINGS**

[0023] Figure 1 shows a prior art drain follower CMOS circuit.

[0024] Figure 2 is a graph illustrating the relationships between input voltage versus through current " $I_d$ " and output voltage for the circuit of Figure 1.

[0025] Figure 3 is a graph illustrating a typical analog signal



waveform.

[0026] Figure 4 shows a typical prior art source follower circuit.

[0027] Figure 5 is a graph illustrating the relationship between input voltage versus through current " $I_d$ " and output voltage for the circuit of Figure 4.

[0028] Figure 6 shows a prior art source follower circuit having a single MOSFET and a load.

[0029] Figure 7 shows a prior art complementary source follower circuit for an LSI.

[0030] Figure 8 is a graph illustrating the dead gap and threshold voltage relationship for the circuit of Figure 7.

[0031] Figure 9 shows a prior art source follower circuit that eliminates the dead gap by input voltage level shifting of the threshold voltage.

[0032] Figure 10 is a graph illustrating the results of the input voltage level shifting of the circuit of Figure 9.

[0033] Figure 11 shows a source follower circuit according to a certain presently preferred embodiment of this invention that eliminates the dead gap by shifting the threshold voltages of the MOSFETs.

[0034] Figure 12 is a graph illustrating the results of the threshold voltage shifting of the circuit of Figure 11.

[0035] Figure 13 shows a source follower circuit illustrating an-

other certain presently preferred embodiment of this invention that combines both threshold voltage shifting and input voltage level shifting.

[0036] Figure 14 is a graph illustrating the results of the threshold voltage shifting and input voltage level shifting of the circuit of Figure 13.

[0037] Figure 15 shows another embodiment of a source follower circuit according to this invention having a single MOSFET and a load.

[0038] Figure 16 is a graph that shows the relationship between input voltage, output voltage, and circuit current  $I_d$ .

[0039] Figure 17 shows a source follower circuit according to this invention where a back bias voltage can shift the threshold voltage of each transistor.

[0040] Figure 18 shows a source follower circuit according to this invention where the back bias voltage can be switched between standby mode and active mode for each transistor.

[0041] Figure 19 is similar to Figure 18, but also includes a level shift circuit.

[0042] Figure 20 shows a source follower circuit according to this invention where the back bias voltage can be independently switched between active mode and standby mode for each transistor.

[0043]

## DETAILED DESCRIPTION

[0044] The present invention can be implemented using conventional MOSFET technology, and the described embodiments can be designed and fabricated in accordance with known CMOS and SOI rules and methodologies. These rules and methodologies are well-known in the art and will not be repeated for this description. SOI materials meeting this criterion are well known in the art.

[0045] In Figure 11, the drain (D) terminal of NFET (N-channel field effect transistor) is connected to positive voltage  $V_{cc}$  and the drain (D) of PFET (P-channel field effect transistor) is connected to lower or negative voltage  $V_{ss}$ . Each transistor has a back bias terminal connected to its body (B). The back bias terminals and the voltage at "OUT" are connected to back bias control circuit, which can independently control the threshold voltage of each transistor at different values in the active mode and in the standby mode. As is well known in the art, the threshold voltage of a transistor can be changed by changing its back bias voltage. See, for example, U.S. Patent No. 6,275,094, Figures 4 and 6 of U.S. Patent No. 6,232,827, Figure 6 of U.S.

Patent No. 6,271,713, and the bias potential generation circuit in Figure 1 of U.S. Patent No. 5,461,338.

[0046] As shown in Figure 12, the back bias control circuit shifts the threshold voltage of each transistor to achieve linearity and eliminate the dead gap. Normally, the threshold voltage of the NFET is shifted less than 0 volts and the threshold voltage of the PFET is shifted more than 0 volts. The crossover point is usually about  $(V_{cc} + V_{ss})/2$ .

[0047] In Figure 13, a level shift circuit is also used in addition to a back bias control circuit. This embodiment can be used when the threshold voltage cannot be shifted enough to achieve linearity. While turning off the level shift circuit will re-create the dead gap so that power is not consumed in standby mode, this can also be accomplished using the back bias control circuit, which may be more effective. Figure 14 shows how the level shift circuit and the back bias control circuit eliminate the dead gap when the source follower circuit is in active mode.

[0048] Figure 15 shows a resistance load source follower circuit. In this embodiment, power consumption in the active mode and in the standby mode is controlled by back bias control circuit. That is, in standby mode and/or when the transistor is in an "off" state, the threshold voltage is in-

creased so that no current flows from  $V_{cc}$  to  $V_{ss}$ .

[0049] Figure 16 shows the results of controlling the back bias voltage for a complementary source follower circuit according to this invention, such as that shown in Figure 11. Curve A shows the dead gap that results when the threshold voltage of both transistors is shifted by the back bias control circuit. In this dead gap condition both transistors are "off." This condition is created by the input condition from  $(V_{cc} + V_{ss})/2 - |V_{thP}|$  to  $(V_{cc} + V_{ss})/2 + V_{thN}$ . Therefore, when the center of the input signal voltage is  $(V_{cc} + V_{ss})/2$  no current flows. This dead gap condition is for the standby mode. The current flow conditions of the curves B and C are for the active mode. In the curve B case, both threshold voltages are zero. This means that when the input voltage is  $(V_{cc} + V_{ss})/2$  ideally no current flows. But since there are fluctuations in the process, it is not realistic to expect that both threshold voltages will be zero and actually current will flow based on the threshold conditions of both transistors. In this condition, linearity between the input signal and the output signal is not achieved near  $(V_{cc} + V_{ss})/2$ . In curve C, current always flows near  $(V_{cc} + V_{ss})/2$  and linearity is achieved for all input conditions. Thus, shifting the back bias voltage from

curve A or B to curve C achieves linearity and shifting from curve C to curve A or B achieves non-linearity. To eliminate the dead gap in active mode and achieve linearity the back bias voltage shifts from curve A to curve B or C.

When in standby mode, the dead gap is created by shifting from curve A or B to curve C.

[0050] Figure 17 is similar to Figure 11 but shows an example of a connection from the back bias circuit to the output voltage. Figure 18 more explicitly shows the circuitry for shifting between active mode and standby mode. Figure 19 combines the features of Figures 13 and 18, showing both a level shift circuit and the circuitry shown in Figure 18. Figure 20 is similar to Figure 18, but shows an alternative circuit design.

[0051] The present invention is also useful when implemented utilizing SOI technology. Indeed, any technology that allows independent control of the threshold voltages of transistors can be utilized with the present invention. As the drawings illustrate, in this invention there is no control signal line connection (i.e., a connection that carries information) from a body terminal to a source terminal, from a body terminal to a drain terminal, or from a back bias circuit to a drain terminal. However, there can be a

power connection from a back bias circuit to a drain terminal to supply voltage to the back bias circuit.

[0052] While the invention has been particularly shown and described with reference to preferred embodiments, it will be understood by those skilled in the art that various changes in form and detail may be made therein without departing from the spirit and scope of the invention.

[0053] EXAMPLE

[0054] A complementary source follower circuit similar to that of Figure 11 could have an NFET with a threshold voltage of 0.2 volts and a PFET with a threshold voltage of -0.2 volts, where  $V_{cc}$  is 0.9 volts and  $V_{ss}$  is -0.9 volts. The level shift circuit could shift the input voltage of the NFET by -0.3 volts and the input voltage of the PFET by 0.3 volts to eliminate the dead gap. Then, in standby mode, the back bias control circuit could shift the threshold voltage of the NFET by 0.3 volts and the threshold voltage of the PFET by -0.3 volts to re-create a dead gap and reduce  $I_d$  to zero.